

BTH-300-R

<Product Descriptions>

- Bluetooth earphone with PTT for walkie talkie or POC APPs
- Built in PTT function button, Cell phone answer (reject) key, and Volume control button
- Embedded 3.5mm jack is compatible with iPhone earphone and many other earphones.
- Long talk time, up to 10 hours.

<Specification>

Dimension: 65mm X 30mm X 12mm

Temp: $-10^{\circ}\text{C} \pm 2^{\circ}\text{C} \sim 50^{\circ}\text{C} \pm 2^{\circ}\text{C}$

Approx. Weight: 21.6g (External earphone is excluded)

- Fully Qualified Bluetooth v4.0.
- Echo cancellation, noise reduction and extended features
- High Quality DAC
- 80MHz RISC MCU and 80MIPS Kalimba DSP
- SBC, MP3, AAC, Fast stream, APTX codec support
- RoHS compliant
- HSP, HFP, A2DP, AVRCP profile supports
- PTT function: built-in
- Talking Range: Bluetooth class 2, 10 meters
- Display LED: Blue and Red
- Power: Max 4dB
- Sensitivity: -90dB
- DC Input: 5 Vdc (std.)
- Standby Current: 6mA
- Battery: 190mAH
- Standby Time: 50 hours
- Talk Time: 10 Hours





1 Microphone
2 3.5mm earphone jack
3 Power and Pairing button



4 LED Indicator
5 Phone answering/
hang-up button



6 PTT button



7 Volume control buttons
8 USB jack
9 Clip



How to use

PIO state	statement
Power S/W long held(>= 1sec)	Device on
Power S/W long held(>= 2.5sec)	Device off
Power S/W long press >6sec	Enter pairing mode from power off
CELL short press	Answer incoming call Hang up outgoing call or active call Play/Pause
CELL long held(>=1sec)	Reserved
VOL+ short press	Volume up
VOL+ long held(>=0.8sec)	Volume up continuously
VOL- short press	Volume down
VOL- long held(>=0.8sec)	Volume down continuously

BTH-300R State and LED Flashing Pattern

LED state	statement
Blue led on : 2 sec , off : 1 sec , repeat	All profiles are standby but not connected with any Cellphone device yet.
Blue led flash every 2 sec	A2DP or HFP is connected.
Blue led flash twice every 2 sec	On A2DP streaming state.
Blue led on : 1 sec , off : 1 sec , repeat	On active call state.
Blue led and red led flash alternative repeat	Enter pairing mode.
Red led On	Battery Charging
Red led Off	Battery Full



BTH-300 External Audio Accessory (Optional)



300-EP63



300-EP31



300-EP67



300-EP68



300-TP15





Pair BTH-300-R with smart phone

1. Make sure BTH-300-R is OFF, and press power switch and hold for 6 seconds
2. BTH-300-R is under pairing mode when you see RED/BLUE led flashing.
3. Start Bluetooth function on your smart phone.
4. Find the device name "BTH-PTT" under Bluetooth column and connect it.
5. Pairing process is completed.

Pair BTH-300-R5 with Bluetooth Dongle

1. Make sure BTH-300-R5 is OFF, and press power switch and hold for 6 seconds
2. BTH-300R is under pairing mode when you see RED/BLUE led flashing.
3. Start Bluetooth pairing process on your dongle or two way radio.
4. The BTH-300-R5 will automatically connect it.
5. Pairing process is completed.

