

Band

AM/FM

Output power

>3W

Modulation

AM 90% / FM: 1,8 KHz ± 0,2 KHz

Export Version

-

Channels

-

Noise Blanker

No

Display

Multifunction blue backlight display

Digital squelch

Yes

Emergency channel

Yes

Frequency Range

26.565-27.99125 MHz

Keypad Lock

No

Mike Connector

6 Pin

Audio output power

>3W

Hi/Lo power

No

Scan

Yes

Quick Channel Selection

Built-in the multifunction display + S-meter external jack

Power supply voltage

DC 12.6 V - DC ±10%

External speaker socket

Yes

Squelch

Yes

S-Meter

External connection

MIC Gain

Yes

RF Gain

Yes

FIL

No

PA - Public Address

Yes

ANL

No

ESP

No

Inside the Box

1 Radio,mike,fixing bracket,fixing screws

Dimensions HxLxP

180x50x150 mm

Weight

1 Kg